

IBM Spectrum Control Base Edition
Version 2.0.1

Release Notes



First Edition (April 2015)

This edition applies to version 2.0.1 of the IBM Spectrum Control Base Edition software package. Newer document editions may be issued for the same product version in order to add missing information or amend typographical errors. The edition is reset to 'First Edition' for every new product version.

© **Copyright IBM Corporation 2013, 2015.**

US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Contents

Overview	1
Compatibility and requirements	1
Supported storage systems	1
Supported operating systems	3
Minimum server hardware requirements	3
Supported VMware platforms	3
Supported browsers	4
CPU and memory consumption on vCenter Orchestrator	4
Change log	4
Version 2.0.1 (April 2015)	4
Version 2.0.0 (March 2015)	5
Known issues	5
Related information and publications	14
Getting information, help, and service	15
Notices	17
Trademarks	19

Overview

IBM® Spectrum Control Base Edition is a centralized server system that consolidates a range of IBM storage provisioning, automation, and monitoring solutions through a unified server platform.

IBM Spectrum Control Base Edition is an improved and enhanced version of the IBM Storage Integration Server. It provides a single server backend location and enables centralized management of IBM storage resources for different virtualization and cloud platforms.

The following solution components, referred to as applications, are included in the software package:

- IBM Storage Provider for VMware VASA – Improves the ability to monitor and automate storage-related operations on VMware platforms. This includes support for VASA 2.0 and Virtual Volumes. In addition, it uses Storage Policy Based Management (SPBM) technology for optimizing the virtual machine provisioning process.
- IBM Storage Enhancements for VMware vSphere Web Client – Integrate into the VMware vSphere Web Client platform and enable VMware administrators to independently and centrally manage their storage resources on IBM storage systems.
- IBM Storage Plug-in for VMware vCenter Orchestrator – Allows VMware administrators to include IBM XIV® discovery and provisioning in their vCenter Orchestrator automation workflows.
- IBM Storage Management Pack for VMware vCenter Operations Manager – Allows VMware administrators to obtain comprehensive monitoring information about the IBM XIV resources that are utilized in their virtualized cloud environment.

You can download the IBM Spectrum Control Base Edition software package at any time from the IBM Fix Central website (www.ibm.com/support/fixcentral).

Compatibility and requirements

This section specifies the compatibility and requirements of version 2.0.1 of IBM Spectrum Control Base Edition.

Note: For information about the compatibility and requirements of previous versions, refer to relevant release notes of the IBM Storage Integration Server.

Supported storage systems

IBM Spectrum Control Base Edition supports different IBM storage systems as listed in the following table.

Storage system	Microcode version	Compatibility note	Supported cloud interface(s)
IBM DS8700	6.3.x		<ul style="list-style-type: none">• IBM Storage Enhancements for VMware vSphere Web Client

Storage system	Microcode version	Compatibility note	Supported cloud interface(s)
IBM DS8800	6.3.x		<ul style="list-style-type: none"> • IBM Storage Enhancements for VMware vSphere Web Client
IBM DS8870	7.0.0, 7.1.0, 7.2.0, 7.3.0, 7.4.0		<ul style="list-style-type: none"> • IBM Storage Enhancements for VMware vSphere Web Client
IBM Flex System® V7000	7.1.0, 7.2.0		<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA • IBM Storage Enhancements for VMware vSphere Web Client
IBM SAN Volume Controller	7.1.0, 7.2.0, 7.3.0, 7.4.0	Microcode 7.3.0 PTF (with security fix) is also supported	<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA • IBM Storage Enhancements for VMware vSphere Web Client
IBM Storwize® V3500	7.1.0, 7.2.0, 7.3.0, 7.4.0	Microcode 7.3.0 PTF (with security fix) is also supported	<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA • IBM Storage Enhancements for VMware vSphere Web Client
IBM Storwize V3700	7.1.0, 7.2.0, 7.3.0, 7.4.0	Microcode 7.3.0 PTF (with security fix) is also supported	<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA • IBM Storage Enhancements for VMware vSphere Web Client
IBM Storwize V5000	7.1.0, 7.2.0, 7.3.0, 7.4.0	Microcode 7.3.0 PTF (with security fix) is also supported	<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA • IBM Storage Enhancements for VMware vSphere Web Client
IBM Storwize V7000	7.1.0, 7.2.0, 7.3.0, 7.4.0	Microcode 7.3.0 PTF (with security fix) is also supported	<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA • IBM Storage Enhancements for VMware vSphere Web Client
IBM Storwize V7000 Unified	1.4.2, 1.4.3, 1.5.0, 1.5.1	Only block storage is supported. File shares and file systems are not supported.	<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA • IBM Storage Enhancements for VMware vSphere Web Client
IBM XIV Storage System	10.2.4.x 11.0.x, 11.1.x, 11.2.x, 11.3.x, 11.4.x, 11.5.x	VMware VASA 2.0 (VVOL) is supported by version 11.5.1 and above.	<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA • IBM Storage Enhancements for VMware vSphere Web Client • IBM Storage Plug-in for VMware vCenter Orchestrator • IBM Storage Management Pack for VMware vCenter Operations Manager
IBM Spectrum Accelerate	11.5.0.b		<ul style="list-style-type: none"> • IBM Storage Enhancements for VMware vSphere Web Client • IBM Storage Plug-in for VMware vCenter Orchestrator
IBM FlashSystem 900	1.2		<ul style="list-style-type: none"> • IBM Storage Provider for VMware VASA

Note: Newer microcode versions may also be compatible. When a newer microcode version becomes available, contact IBM Support to inquire whether the new microcode version is compatible with version 2.0.1 of IBM Spectrum Control. Alternatively, check for a newer version of IBM Spectrum Control.

Supported operating systems

The IBM Spectrum Control Base Edition software can be installed on the following Linux versions.

Operating system	Architecture
Red Hat Enterprise Linux (RHEL) 6.3 – 6.5	x64

Minimum server hardware requirements

The Linux server upon which IBM Spectrum Control Base Edition is installed should meet the following minimum hardware requirements:

- 64-bit dual-core CPU
- At least 4 GB of RAM
- At least 16 GB of free disk space

The same requirements apply if a virtual machine is used instead of a physical server.

Note:

- For best performance, use a dedicated server.
 - The minimum requirements are for supporting up to 20 storage arrays and up to 1000 objects (storage pools, volumes, hosts, mappings, snapshots, mirroring groups, consistency groups).
-

Supported VMware platforms

Version 2.0.1 of IBM Spectrum Control Base Edition supports the following VMware platforms and frameworks.

VMware platform or framework	Version
vSphere Web Client Server	5.1, 5.5.x, 6.0
vSphere APIs for Storage Awareness (VASA)	5.0, 5.1, 5.5.x, 6.0
vCenter Server Appliance (VCSA)	5.5.x, 6.0
vCenter Operations Manager (vCOPs)	5.8.x
vCenter Orchestrator (vCO)	5.1.x, 5.5.x
vCloud Automation Center (vCAC)	5.x

Note:

- The IBM Storage Enhancements for VMware vSphere Web Client are automatically deployed and enabled by registering vCenter servers on Spectrum Control.
- The IBM Storage Plug-in for VMware vCenter Orchestrator is deployed by installing its plug-in package on the vCenter Orchestrator server.
- The IBM Storage Management Pack for VMware vCenter Operations Manager is deployed by installing its PAK file on the vCenter Operations Manager server.

For more information, refer to the user guide.

Supported browsers

IBM Spectrum Control Base Edition can be accessed and managed with the following web browsers:

- Microsoft Internet Explorer 10.0 or later.
- Mozilla Firefox 21.0 or later.
- Google Chrome 39.0 or later.

The required screen resolution for GUI management is 1024×768 or higher.

CPU and memory consumption on vCenter Orchestrator

When the IBM Storage Plug-in for VMware vCenter Orchestrator is used, the CPU and memory consumption impact on the vCenter Orchestrator server is minimal: approximately 2% CPU usage at peak, and less than 1% memory usage.

The server environment on which the IBM Storage Plug-in for VMware vCenter Orchestrator was tested included:

- CPU: 2 vCPU, Intel Xeon X5650 @ 2.67GHz
- Memory: 3088 MB

Change log

This section summarizes the changes that were made in released version of IBM Spectrum Control Base Edition.

Version 2.0.1 (April 2015)

Version 2.0.1 replaces version 2.0.0 and introduces support for IBM DS8870. In addition, version 2.0.1 resolves the following issues.

Ticket ID	Description
HSGSVR-262521	Fixed: Backup and restore operations are not available.
HSGSVR-262815	Fixed: A storage resource can be created on a managed domain and non-VVOL-enabled service.
VWC-261791	Fixed: IBM Storage Enhancements for VMware vSphere Web Client are missing from the Actions menu of vWC, running under vSphere 6.

Version 2.0.0 (March 2015)

Version 2.0.0 of IBM Spectrum Control Base Edition was the first released version, supporting a range of IBM storage systems and including the following features and primary components:

- Newly designed, powerful and intuitive web management interface with improved usability and superb user experience.
- **IBM Storage Provider for VMware VASA**, improving ability to monitor and automate storage-related operations on VMware platforms. This includes support for VMware virtual volumes (VVOLs), with XIV v11.5.1, and for Storage Policy Based Management (SPBM).
- **IBM Storage Enhancements for VMware vSphere Web Client**, allowing VMware administrators to self-provision volumes (LUNs) in selected storage pools that were predefined by the storage administrators. The volumes are mapped to ESXi hosts, clusters, or datacenters as logical drives that can be used for storing VMware datastores (virtual machine data containers).
- **IBM Storage Plug-in for VMware vCenter Orchestrator**, allowing VMware administrators to include IBM storage discovery and provisioning in their vCenter Orchestrator (vCO) automation workflows.
- **IBM Storage Management Pack for VMware vCenter Operations Manager**, allowing Operations Manager users to obtain comprehensive monitoring information about the IBM storage resources that are utilized in their virtualized environment.

Known issues

This section details the known issues in version 2.0.1 of IBM Spectrum Control Base Edition and its solution components, along with possible solutions or workarounds (if available).

Table 1. Known issues in IBM Spectrum Control Base Edition

Ticket ID	Component	Description
HSGSVR-261496	IBM Spectrum Control Base Edition	<p>Volumes that were migrated from an XIV storage array (A) to another XIV storage array (B) using Hyper-Scale Mobility (online volume migration) might not be manageable.</p> <p>This specifically occurs if the volumes on the original XIV storage array (A) are deleted from the storage array (A), and then the same volume IDs are reused on that storage array (A).</p> <p>If both XIV systems (A and B) are connected to the same Spectrum Control and this situation occurs, it prevents the management of these volumes through Spectrum Control.</p> <p>Currently there is no solution or workaround for this limitation.</p>

Table 1. Known issues in IBM Spectrum Control Base Edition (continued)

Ticket ID	Component	Description
HSGSVR-261731	IBM Spectrum Control Base Edition	<p>DS8000® storage array information is not updated on the Spectrum Control side after a connectivity break, or if the storage admin user group has been modified on the DS8000 side.</p> <p>To resolve this issue, restart the Spectrum Control service:</p> <pre>service ibm_spectrum_control restart</pre>
HSGSVR-261745	IBM Spectrum Control Base Edition	<p>For Storwize V7000 Unified storage arrays, the microcode version number, build number, and system ID number are not consistent when appearing in the Integration Server, vSphere Web Client, and storage system management GUIs. Different version numbers and system IDs are displayed on each platform.</p> <p>Currently there is no solution or workaround for this limitation.</p>
HSGSVR-261753	IBM Spectrum Control Base Edition	<p>The registration of the Spectrum Control as a VASA storage provider on the vCenter Server side might fail if an expired self-signed SSL certificate is present on Spectrum Control.</p> <p>To resolve this issue, replace the self-signed certificate as explained in the user guide.</p>
HSGSVR-261771	IBM Spectrum Control Base Edition	<p>Whenever a directory-based storage admin fails to log in (from the Spectrum Control side) to any storage array that is in use, Spectrum Control immediately locks the storage admin user account and all storage arrays become inaccessible on the Spectrum Control side.</p> <p>This is to prevent repeated login attempt failures after which the directory server blocks that user account.</p> <p>In such a case, update the storage admin credentials on the storage array with which the login has failed. Alternatively, you can remove that specific storage array from Spectrum Control and then reset the credentials.</p> <p>You can find the relevant storage array by checking the events.log log file. For example:</p> <pre>Mar 26 13:50:01 ronend-scl ERROR ID:SC-0008 Severity:ERROR Parameters:reason=Logging in to array 2810-214-MN65025 has failed with the provided credentials. ,user_name=ronenu Message:Storage credentials for user ronenu were disabled. Reason: Logging in to array 2810-214-MN65025 has failed with the provided credentials.</pre>

Table 1. Known issues in IBM Spectrum Control Base Edition (continued)

Ticket ID	Component	Description
HSGSVR-261778	IBM Spectrum Control Base Edition	<p>After an upgrade or reinstallation of Spectrum Control , some DS8000 or SAN Volume Controller storage array identifiers might change, causing Spectrum Control to stop synchronizing with these storage arrays.</p> <p>To resolve this issue, use the Spectrum Control GUI or CLI to remove and then add back these storage arrays.</p>
HSGSVR-261888	IBM Spectrum Control Base Edition	<p>The Collect Log GUI option does not work on Microsoft Internet Explorer 10 or 11.</p> <p>To resolve this issue, disable the Internet Explorer Enhanced Security Configuration option.</p>
HSGSVR-261942	IBM Spectrum Control Base Edition	<p>If the IP address of a storage array changes, the sc_storage_array CLI command is unable to update the IP address of the storage array.</p> <p>In such a case, use the Spectrum Control GUI to edit and update the IP address of the storage array (In the Arrays pane, move the mouse pointer over an array that you want to update, and then click the Edit button).</p>
HSGSVR-262136	IBM Spectrum Control Base Edition	<p>In some cases, the Celery service might hang when it is stopped.</p> <p>To resolve this issue, terminate the Celery background process by using the Linux kill -9 command.</p>
HSGSVR-262165	IBM Spectrum Control Base Edition	<p>When the XIV storage credentials are of an XIV domain administrator (supported by XIV microcode version 11.5 or later), volume mapping might return the 'LUN already in use' error message.</p> <p>This occurs if the LUN number is already associated with a volume outside of the XIV domain.</p> <p>Currently there is no solution or workaround for this limitation.</p>

Table 1. Known issues in IBM Spectrum Control Base Edition (continued)

Ticket ID	Component	Description
HSGSVR-262175	IBM Spectrum Control Base Edition	<p>When an XIV array configuration includes a cluster with no hosts (empty cluster), a volume created from vSphere Web Client or vCenter Orchestrator is mapped to that cluster in addition to any specified host mapping.</p> <p>As a result, volumes that were mapped to an empty cluster must be manually unmapped.</p> <p>To avoid this issue: before mapping volumes to an XIV array, delete all empty cluster configurations on that array, or add at least one host to each empty cluster.</p>
HSGSVR-262194	IBM Spectrum Control Base Edition	<p>The DS8000 proxy service fails to stop during uninstallation or upgrade.</p> <div data-bbox="781 747 1419 852" style="border: 1px solid black; border-radius: 10px; padding: 5px;"> <pre>Stopping Django service ... [OK] Stopping Celery services ... [OK] Stopping DS8K proxy.....[FAILED]</pre> </div> <p>To resolve this issue, terminate all the Java™ background processes and then restart the Spectrum Control service.</p>
HSGSVR-262279	IBM Spectrum Control Base Edition	<p>Spectrum Control fails to lock out a storage admin user account with LDAP credentials after an unsuccessful login attempt.</p> <p>Currently there is no solution or workaround for this limitation.</p>
HSGSVR-262573	IBM Spectrum Control Base Edition	<p>RESTful API may not display the correct number of storage array IP interfaces.</p> <p>Currently there is no solution or workaround for this limitation.</p>
HSGSVR-262632	IBM Spectrum Control Base Edition	<p>A long-running RESTful API task, such as phase-in, phase-out, etc, may not update its current state, if Spectrum Control service has been restarted during its operation.</p> <p>Currently there is no solution or workaround for this limitation.</p>
HSGSVR-262655	IBM Spectrum Control Base Edition	<p>If a vCenter server is disconnected from Spectrum Control during the upgrade, the vWC extension appears with the previous version, when the vCenter server is re-activated.</p> <p>To resolve this issue, remove and reattach the vCenter server on Spectrum Control.</p>

Table 1. Known issues in IBM Spectrum Control Base Edition (continued)

Ticket ID	Component	Description
HSGSVR-262723	IBM Spectrum Control Base Edition	<p>Spectrum Control fails to pull updates from the storage array, if the internal clock of its server is set back.</p> <p>To avoid this issue, set the Spectrum Control server clock to the correct time before the installation.</p>
HSGSVR-262725	IBM Spectrum Control Base Edition	<p>XIV hosts appear in vWC as disconnected because of a mismatch between the XIV domain policy and the host domain settings. When a host without a domain added to the XIV in the open domain policy mode, it becomes inaccessible, if the XIV domain access policy is changed to Closed.</p> <p>To resolve this issue, delete all hosts defined without domain, and add these hosts again with valid domain settings.</p>
HSGSVR-262762	IBM Spectrum Control Base Edition	<p>Spectrum Control cannot use IPv6 addresses for management connection to the XIV storage systems.</p> <p>To resolve this issue, use IPv4 addressing, when configuring storage arrays.</p>
HSGSVR-262847	IBM Spectrum Control Base Edition	<p>Disconnected storage array disappear from the Spectrum Control web interface after the upgrade.</p> <p>To avoid this issue, before performing upgrade, verify that all storage arrays are connected to Spectrum Control properly.</p>

Table 2. Known issues in IBM Storage Provider for VMware VASA

Ticket ID	Component	Description
VVOLVP-261037	IBM Storage Provider for VMware VASA	<p>VASA 2.0 fails to connect to a storage array if only management port 1 is down and the rest of the management ports are available.</p> <p>Currently there is no solution or workaround for this limitation.</p>

Table 2. Known issues in IBM Storage Provider for VMware VASA (continued)

Ticket ID	Component	Description
VASAVP-261237	IBM Storage Provider for VMware VASA	<p>When the IBM Storage Provider for VMware VASA and the IBM Tivoli® Storage Productivity Center (TPC) storage provider are registered on the same VMware vCenter server, while the same storage array is configured for both, vCenter uses IBM Tivoli Storage Productivity Center provider as the only source of information for that array's storage views on vSphere Client.</p> <p>In such a case, determine whether the IBM Tivoli Storage Productivity Center capabilities are sufficient for replacing the IBM Storage Provider for VMware VASA. If the IBM Storage Provider for VMware VASA is still needed, IBM TPC 5.2 (or later) provides a method of excluding storage arrays from a specific storage provider, allowing you to remove the array association with the IBM TPC provider.</p> <p>For more information, refer to the IBM Tivoli Storage Productivity Center documentation.</p>
VASAVP-261268	IBM Storage Provider for VMware VASA	<p>If spaces are included in the IP interface name (iSCSI) of an XIV storage array, that XIV array cannot be monitored by the IBM Storage Provider for VMware VASA, and information of that XIV array is not visible to the relevant vCenter server.</p> <p>To avoid this issue, do not include spaces in the IP interface name of the XIV storage array.</p>
VVOLVP-261511	IBM Storage Provider for VMware VASA	<p>A storage space with a VVOL-enabled service deleted from a primary Spectrum Control in an HA group, still exists in the standby Spectrum Control.</p> <p>To resolve this issue, delete the space and the service from the standby Spectrum Control manually.</p>
VVOLVP-261531	IBM Storage Provider for VMware VASA	<p>If an array is removed and added to Spectrum Control after its storage resource was added to a VVOL-enabled service, its previous configuration is not preserved after the addition. This occurs if Spectrum Control is not registered as a VASA provider.</p> <p>To avoid this issue, verify that Spectrum Control is registered as a VASA provider before adding the array after its removal. In addition, after the array is added, it is recommended to check the vCenter log whether Spectrum Control was identified as an active VASA provider.</p>

Table 2. Known issues in IBM Storage Provider for VMware VASA (continued)

Ticket ID	Component	Description
HSGSVR-262638	IBM Storage Provider for VMware VASA	<p>VASA 1 trusted certificates cannot be revoked, using the Spectrum Control web interface.</p> <p>To resolve this issue, unregister Spectrum Control as a storage provider on the vCenter server.</p>
HSGSVR-262750	IBM Storage Provider for VMware VASA	<p>Spectrum Control does not generate an error message, when a storage service with a certain capability is attached to a storage array, which does not support the required capability.</p> <p>To avoid this issue, verify that both service and storage array have matching capabilities before the attachment.</p>

Table 3. Known issues in IBM Storage Enhancements for VMware vSphere Web Client

Ticket ID	Component	Description
VWC-261324	IBM Storage Enhancements for VMware vSphere Web Client	<p>If a combination of both iSCSI and FC initiator port types is defined for an ESXi host, mapping volumes to that ESXi host causes both iSCSI and FC to be used for those volumes.</p> <p>To avoid this situation, use the storage system management tools to define only one active protocol type (iSCSI or FC) for the initiators of each ESXi host.</p>
VWC-261530	IBM Storage Enhancements for VMware vSphere Web Client	<p>When using the storage system management GUI (as opposed to the IBM Storage Enhancements GUI in vSphere Web Client) to map a single volume to more than one ESXi hosts using different LUN IDs, the volume is not properly recognized by vSphere Web Client and cannot be managed by the IBM Storage Enhancements. In addition, multiple errors might occur on the vSphere Web Client during the use or modification of that volume.</p> <p>To avoid this issue, always use the same LUN ID when mapping a volume to multiple ESXi hosts via the storage system management GUI.</p>
VWC-261542	IBM Storage Enhancements for VMware vSphere Web Client	<p>The Manage > Host Mapping tab of the IBM Storage Volume object shows incorrect mapping information. Hosts that cannot access the datastore are shown as not being mapped to the LUN.</p> <p>Currently there is no solution or workaround for this limitation.</p>

Table 3. Known issues in IBM Storage Enhancements for VMware vSphere Web Client (continued)

Ticket ID	Component	Description
VWC-261713	IBM Storage Enhancements for VMware vSphere Web Client	<p>If a volume is mapped to more than one ESXi host while a virtual machine on one of these hosts uses this volume as an RDM LUN, the volume information might not be displayed correctly in vSphere.</p> <p>Currently there is no solution or workaround for this limitation.</p>
VWC-261724	IBM Storage Enhancements for VMware vSphere Web Client	<p>If a volume is mapped to two or more ESXi hosts that are managed by more than one vCenter server, volume operations fail.</p> <p>To avoid this issue, do not map a specific volume to ESXi hosts that are not managed by the same vCenter server.</p>
VWC-261752	IBM Storage Enhancements for VMware vSphere Web Client	<p>Error message 'Could not connect to vSphere Web Client server' appears if the Spectrum Control software is upgraded without first logging out from vSphere Web Client.</p> <p>To avoid this error on the Spectrum Control side, log out of vSphere Web Client before upgrading the Spectrum Control software.</p>
VWC-261759	IBM Storage Enhancements for VMware vSphere Web Client	<p>If the host_rescan_timeout parameter value is changed to 1 in the <code>vwc_config.ini</code> configuration file (on Spectrum Control), volume creation and mapping operations might fail.</p> <p>To avoid this issue, keep the default value of 300 or keep the value higher than 1.</p>
VWC-261760	IBM Storage Enhancements for VMware vSphere Web Client	<p>When deleting a volume that is mapped to a host, the mapping is removed but the volume is not deleted. No indication is given on vSphere Web Client that the volume still exists.</p> <p>To avoid this issue, unmap the volume before deleting it.</p>
VWC-261765	IBM Storage Enhancements for VMware vSphere Web Client	<p>DS8000 volume creation might fail when mapping multiple volume groups to one ESXi host.</p> <p>If you encounter this problem, configure only one volume group for one ESXi host when creating and mapping a volume.</p>
VWC-261793	IBM Storage Enhancements for VMware vSphere Web Client	<p>VMware vSphere Web Client fails to initialize in the vSphere 6 environment, displaying an error message.</p> <p>To avoid this issue, manually add port 9443 to the URL, when launching vSphere Web Client. Use the following format <code>https://<host>:9443/vsphere-client</code>.</p>

Table 3. Known issues in IBM Storage Enhancements for VMware vSphere Web Client (continued)

Ticket ID	Component	Description
VWC-261795	IBM Storage Enhancements for VMware vSphere Web Client	<p>A volume cannot be moved to or from a child storage pool on IBM Spectrum Virtualize (7.4), using vSphere Web Client.</p> <p>Currently there is no solution or workaround for this limitation.</p>
VWC-261802	IBM Storage Enhancements for VMware vSphere Web Client	<p>A vCenter server that receives a new IP address retains information about storage resources of a Spectrum Control connected to it prior to the address change. If the vCenter server is added to another Spectrum Control instance, the previously connected arrays and pools remain visible in the vWC.</p> <p>To resolve this issue, log into vCenter Managed Object Browser (MOB) at <a href="https://<vCenter_server_IP>/mob">https://<vCenter_server_IP>/mob., using your vCenter credentials.</p> <p>Navigate to Content > ExtensionManager > UnregisterExtension.</p> <p>Enter <code>com.ibm.storage.vwc</code>, when a pop-up window is displayed, and click Invoke Method twice.</p> <p>Repeat registration of the vCenter server on the newly connected Spectrum Control.</p>

Table 4. Known issues in IBM Storage Plug-in for VMware vCenter Orchestrator

Ticket ID	Component	Description
VCOPLUGIN-133	IBM Storage Plug-in for VMware vCenter Orchestrator	<p>Due to a known issue in VMware vCenter Orchestrator, title texts are displayed improperly after clicking the IBM Storage tab.</p> <p>Currently there is no solution or workaround for this limitation.</p>
VCOPLUGIN-162	IBM Storage Plug-in for VMware vCenter Orchestrator	<p>If the Map workflow uses initiators that are not configured on the storage array, the workflow succeeds even though the initiators are silently ignored.</p> <p>Currently there is no solution or workaround for this limitation.</p>

Table 5. Known issues in IBM Storage Management Pack for VMware vCenter Operations Manager

Ticket ID	Component	Description
HSGSVR-262168	IBM Storage Management Pack for VMware vCenter Operations Manager	<p>Not all XIV informational-level severity events are reported by Spectrum Control to vCenter Operations Manager.</p> <p>Note: All other XIV severity events (Warning, Minor, Major, Critical) are reported.</p> <p>Currently there is no solution or workaround for this limitation.</p>
VCOP-244615	IBM Storage Management Pack for VMware vCenter Operations Manager	<p>The thresholds reported to the vCOPs server are tailored for XIV microcode version 11.2 or later, but not for earlier XIV microcode versions.</p> <p>To resolve this issue, manually update to the thresholds in vCOPs to match the XIV microcode that you are using.</p>
VCOP-244666	IBM Storage Management Pack for VMware vCenter Operations Manager	<p>If a storage object name contains spaces, it is displayed in the vCOPs custom view with underlines instead of spaces.</p> <p>Currently there is no solution or workaround for this limitation.</p>
VCOP-244801	IBM Storage Management Pack for VMware vCenter Operations Manager	<p>Duplicate thresholds might be appear in vCOPs if a vCOPs server was removed from Spectrum Control and then re-added.</p> <p>To resolve this issue, delete the duplicate thresholds.</p>
VCOP-244802	IBM Storage Management Pack for VMware vCenter Operations Manager	<p>If the vCOPs server becomes unreachable while Spectrum Control is still reporting to it, the reporting ceases when the vCOPs server becomes reachable again.</p> <p>To resolve this issue, restart the Spectrum Control service.</p>

Related information and publications

You can find additional information and publications related to IBM Spectrum Control Base Edition on the following information sources.

- IBM Knowledge Center (ibm.com/support/knowledgecenter)
- IBM DS8700 on IBM Knowledge Center (ibm.com/support/knowledgecenter/STUVMB)
- IBM DS8800 on IBM Knowledge Center (ibm.com/support/knowledgecenter/STXN8P)
- IBM DS8870 on IBM Knowledge Center (ibm.com/support/knowledgecenter/ST8NCA)
- IBM Flex System Information Center (publib.boulder.ibm.com/infocenter/flexsys/information)
- IBM SAN Volume Controller on IBM Knowledge Center (ibm.com/support/knowledgecenter/STPVGU)

- IBM Storwize V3500 on IBM Knowledge Center (ibm.com/support/knowledgecenter/STLM6B)
- IBM Storwize V3700 on IBM Knowledge Center (ibm.com/support/knowledgecenter/STLM5A)
- IBM Storwize V5000 on IBM Knowledge Center (ibm.com/support/knowledgecenter/STHGUJ)
- IBM Storwize V7000 on IBM Knowledge Center (ibm.com/support/knowledgecenter/ST3FR7)
- IBM Storwize V7000 Unified on IBM Knowledge Center (ibm.com/support/knowledgecenter/ST5Q4U)
- IBM XIV Storage System on IBM Knowledge Center (ibm.com/support/knowledgecenter/STJTAG)
- IBM Spectrum Accelerate on IBM Knowledge Center (ibm.com/support/knowledgecenter/STZSWD)
- IBM FlashSystem 900 on IBM Knowledge Center (ibm.com/support/knowledgecenter/STKMQB)
- VMware Documentation (vmware.com/support/pubs)
- VMware Product Support (vmware.com/support)
- VMware Knowledge Base (kb.vmware.com)

Getting information, help, and service

If you need help, service, technical assistance, or want more information about IBM products, you can find various sources to assist you. You can view the following websites to get information about IBM products and services and to find the latest technical information and support.

- IBM website (ibm.com[®])
- IBM Support Portal website (www.ibm.com/storage/support)
- IBM Directory of Worldwide Contacts website (www.ibm.com/planetwide)

Notices

These legal notices pertain to IBM Storage Host Software Solutions product documentation.

This information was developed for products and services offered in the U.S.A.

IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not grant you any license to these patents. You can send license inquiries, in writing, to:

*IBM Director of Licensing
IBM Corporation
North Castle Drive
Armonk, NY 10504-1785
U.S.A.*

For license inquiries regarding double-byte character set (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

*Intellectual Property Licensing
Legal and Intellectual Property Law
IBM Japan Ltd.
1623-14, Shimotsuruma, Yamato-shi
Kanagawa 242-8502 Japan*

The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law:

INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Any references in this information to non-IBM Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this IBM product and use of those Web sites is at your own risk.

IBM may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

*IBM Corporation
Attn: Office of Legal Counsel
650 Harry Road
San Jose, CA 95120-6099
U.S.A.*

Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this document and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement or any equivalent agreement between us.

Any performance data contained herein was determined in a controlled environment. Therefore, the results obtained in other operating environments may vary significantly. Some measurements may have been made on development-level systems and there is no guarantee that these measurements will be the same on generally available systems. Furthermore, some measurements may have been estimated through extrapolation. Actual results may vary. Users of this document should verify the applicable data for their specific environment.

Information concerning non-IBM products was obtained from the suppliers of those products, their published announcements or other publicly available sources. IBM has not tested those products and cannot confirm the accuracy of performance, compatibility or any other claims related to non-IBM products. Questions on the capabilities of non-IBM products should be addressed to the suppliers of those products.

All statements regarding IBM's future direction or intent are subject to change or withdrawal without notice, and represent goals and objectives only.

This information contains examples of data and reports used in daily business operations. To illustrate them as completely as possible, the examples include the names of individuals, companies, brands, and products. All of these names are fictitious and any similarity to the names and addresses used by an actual business enterprise is entirely coincidental.

Trademarks

IBM, the IBM logo, and ibm.com are trademarks or registered trademarks of International Business Machines Corp., registered in many jurisdictions worldwide. Other product and service names might be trademarks of IBM or other companies. A current list of IBM trademarks is available on the Copyright and trademark information website (www.ibm.com/legal/us/en/copytrade.shtml).

VMware, ESX, ESXi, vSphere, vCenter, and vCloud are trademarks or registered trademarks of VMware Corporation in the United States, other countries, or both.

Microsoft, Windows Server, Windows, and the Windows logo are trademarks or registered trademarks of Microsoft Corporation in the United States, other countries, or both.

Linux is a trademark of Linus Torvalds in the United States, other countries, or both.

Other product and service names might be trademarks of IBM or other companies.



Printed in USA